



The Elite VSX-LX505 creates the soundscape of **IMAX® Enhanced** and Dolby Atmos®/DTS:X ideally calibrated with **Advanced MCACC**, and even provides similar sound effects with **Dolby Atmos Height Virtualizer** without additional surround speakers. Enjoy spectacles from next-gen video/gaming standards with support for **HDMI 2.1*1** with 8K pass-through, VRR, ALLM and QFT, HDCP 2.3, or stream songs across the house with Multi Zone Music, SONOS system, Chromecast built-in, DTS Play-Fi®, and **Apple AirPlay 2**. Don't forget it also features Powered Zone 2/Zone 3 Audio, up to 11.2 MHz DSD direct playback, 2 HDMI outputs and Roon Tested certification. Finally, it **works with Alexa** for voice control.

Amplification

- > Channels: 9
- > Amplification Type: Direct Energy
- > 230 W/ch (6 ohms, 1 kHz, THD 10 %, 1ch Driven)
- > 120 W/ch (8 ohms, 20 Hz-20 kHz, THD 0.08 %, 2ch Driven FTC)

Audio Features

- > **IMAX Enhanced**
- > Dolby Atmos®, Dolby Surround Upmixer supports DTS Formats
- > DTS:X®, DTS Neural:X® Upmixer supports Dolby Formats
- > Reflex Optimizer
- > **Dolby Atmos Height Virtualizer**
- > Dolby® TrueHD, Dolby Digital Plus
- > DTS-HD Master Audio, DTS-HD High Resolution Audio, DTS 96/24, DTS-ES, DTS Express
- > DSD Direct Playback via Network/USB (11.2, 5.6, 2.8 MHz/2 ch)
- > DSD Disc (SACD) Playback via HDMI (2.8 MHz/2 ch, 5.1 ch)
- > Digital Quad-Core 32-bit DSP (Cirrus Logic) + Aureus™ floating-point DSP (TI)
- > 192 kHz/24-bit D/A Conversion
- > **Enhanced Audio Return Channel (eARC) on HDMI Out (Main)**
- > **Advanced MCACC Auto Room Tuning**
 - Auto Phase Control Plus
 - Subwoofer EQ
 - Multi-point Standing Wave Control
- > Dirac Live® Room Correction
- > Advanced Sound Retriever (2ch)
- > Advanced Surround Modes
 - Classical, Unplugged, Entertainment Show, Drama, Advanced Game, Action, Rock/Pop, Sports, Extended Stereo, Mono Music, Front Stage Surround Advance

Video Features

- > Support HDMI 2.1*1 with 8K Pass-through, VRR (Variable Refresh Rate), ALLM (Auto Low Latency Mode), QFT (Quick Frame transport), DSC (Display Stream Compression), QMS (Quick Media Switching), and eARC (Main Out)

- > Supports HDR10+, HDR10, and HLG; 4:4:4/24-bit and BT.2020 color; DeepColor™ (36-bit), "x.v.Color", LipSync, and HDCP 2.3
- > Dolby Vision Compatible
- > Ultra HD Upscaling (4K to 8K, 1080p to 8K/4K)
- > 3D Ready (Blu-ray Disc™, Broadcast, and Games)

Home Network Features

- > Works with Alexa to control audio
- > Works with Hey Google and Chromecast built-in
- > DTS Play-Fi with Pioneer Music Control App supporting Hi-Res Audio Playback
- > **Apple AirPlay 2** with Siri Voice Control
- > Works with SONOS supporting multiple Sonos Connect control and Volume Pass Through mode
- > Amazon Music, Pandora®, Spotify, TIDAL, and Deezer Hi-Fi Music-Streaming Services Ready*2
- > Internet Radio with TuneIn
- > Hi-Res Audio File Playback via USB/Network
- > Up to 192 kHz/24-bit ALAC*3, AIFF, FLAC, WAV (RIFF) and **11.2 MHz DSD*4**

Convenience Features

- > **Personal Preset**
- > **Dialog Enhancement**
- > Dual Band (5 GHz/2.4 GHz) Wi-Fi® Built-in
- > Bluetooth® Wireless Technology Transmitter/Receiver (Version: 4.2, Profile: A2DP 1.2/AVRCP 1.3, Codec: SBC/aptX/aptX HD (TX), SBC/AAC(RX)) Built-in
- > Pioneer Remote App*5 Ready for Multi-room Entertainment Control and Network Streaming
- > User-Friendly GUI with System Setup Menu
- > On-Screen Information for Audio/Video Status
- > Web Setup
- > Auto Power Off in HDMI Standby Through
- > AM/FM Tuner 40 Presets
- > Sleep Timer
- > User-Friendly Simple Remote Control

Front Terminals

- > HDMI 1 In
- > USB 1 In for USB Drive
- > MCACC/Dirac Live Setup MIC In
- > Phones 1 Out (Gold-Plated)

Rear Terminals

- > HDMI 6 In (4 Assignable)
- > HDMI 2 Out (1 for MAIN, 1 for SUB/Dirac Live)
- > Ethernet 1 In
- > USB 1 In for USB Drive
- > AV (Component) 1 In (Assignable)
- > AV (Composite) 2 In (Assignable)
- > Audio 1 In (Assignable)

- > Phono (MM) 1 In
- > Digital Coaxial 1 In (Assignable)
- > Digital Optical 1 In (Assignable)
- > FRONT, CENTER, SURROUND, HEIGHT 1, SURROUND BACK, SUBWOOFER x 2 Pre Out
- > **ZONE 2 Pre/Line Out/ZONE B Line Out**
- > ZONE 3/HEIGHT 2 Pre/Line Out
- > Speaker 11ch Out (FRONT, CENTER, SURROUND, HEIGHT 1/Bi-AMP, SURROUND BACK/ZONE 3/HEIGHT 2, ZONE 2)
- > IR 1 In/1 Out
- > 12 V Trigger 2 Out
- > RS-232C
- > FM/AM Antenna

Specifications

- > Power Requirements: AC 120 V, 60 Hz
- > Power Consumption/Standby: 850 W/0.15 W
- > Dimensions (W x H x D): 17-1/8 x 7-5/16 x 15-3/16 inches (435 x 185 x 386 mm)
- > Weight: 28.7 lbs. (13 kg)
- > Carton Dimensions: 21-5/16 x 12-3/16 x 19-3/16 inches (541 x 310 x 487 mm)
- > Carton Included Weight: 35.3 lbs. (16.0 kg)

*1 HDMI in 1-6 *2 Service availability depends on country or region *3 Up to 96 kHz supported via wireless LAN
 *4 Converted to PCM. Not guaranteed via wireless LAN *5 Available for free download from the App Store/The Google Play



VSX-LX505(B) UPC: 889951003441

HDMI 2.1 for a powerful viewing and gaming experience

HDMI 2.1 ensures all HDMI terminals support 8K (60p/4:4:4/24-bit) video passthrough to compatible displays, as well as HDCP 2.3 so you will have no problem when upgrading to new devices. HDMI 2.1 also supports VRR (Variable Refresh Rate) to eliminate lag, stutter and frame-tearing to deliver a fluid gaming experience. Various enhancements such as ALLM (Auto Low Latency Mode) and QFT (Quick Frame Transport) help to optimize latency and further limit lag to ensure you'll always be on top of your game.



IMAX Enhanced

The VSX-LX505 is IMAX Enhanced, certified to deliver the dynamic and heart-pounding sound presented by DTS just as intended by the filmmaker, and provide an immersive experience on your home theater.



Dolby Atmos®/Dolby Surround Upmixing

By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch to drive the 7.2.4ch configuration of Dolby Atmos®. You can reproduce object-oriented sound in smooth, curving movements, or the realistic three-dimensional movement overhead by the top speakers. Other audio codecs such as PCM and DSD can be upmixed using Dolby Surround for enjoying 3D surround sound.



Dolby Atmos 7.2.4ch Speaker System



DTS:X®/DTS Neural:X Upmixing

DTS:X is the next-generation audio codec from DTS that leverages object-based audio to enable new immersive and interactive audio experiences. By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch for driving a 7.2.4ch surround system. Experience an immersive soundscape with incredibly rich and life-like audio. Other audio codecs such as PCM and DSD can be upmixed using DTS Neural:X for enjoying 3D surround sound.



DTS:X 7.2.4ch Speaker System



Dolby Atmos Height Virtualization

When playing any Dolby format, engaging the Dolby Atmos Height Virtualizer enables a more immersive listening experience, creating a virtual surround and height effect from traditional speaker layouts without employing additional surround or height speakers.

Integrated Technologies



*PIONEER, MCACC, Phase Control, Advanced Sound Retriever, and the logos are registered trademarks of Pioneer Corporation, and are used under license. *The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator Inc. in the United States and other countries. *Dolby, Dolby Atmos, Dolby Surround, Dolby Vision, and the double-D symbol are registered trademarks of Dolby Laboratories. *Manufactured under license from IMAX Corporation. IMAX® is a registered trademark of IMAX Corporation in the United States and/or other countries. All Rights Reserved. *For DTS patents, see <http://patents.dts.com>. Manufactured under license from DTS, Inc. DTS, the Symbol, DTS and the Symbol together, DTS:X, Play-Fi, the DTS:X logo, and the DTS Play-Fi logo, are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. © DTS, Inc. All Rights Reserved. *Apple, AirPlay and Siri are trademarks of Apple Inc., registered in the U.S. and other countries. *App Store is a service mark of Apple Inc. *Wi-Fi® is a registered trademark of the Wi-Fi Alliance. The Wi-Fi CERTIFIED Logo is a certification mark of the Wi-Fi Alliance. *The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. *x.v.Color™ is a trademark of Sony Corporation. *Pandora, the Pandora logo, and the Pandora trade dress are trademarks or registered trademarks of Pandora Media, Inc. used with permission. *Spotify and the Spotify logo are trademarks of the Spotify Group, registered in the U.S. and other countries. *The product with the Hi-Res Audio logo is conformed to Hi-Res Audio standard defined by Japan Audio Society. The logo is used under license from Japan Audio Society. *Blu-ray Disc™, Blu-ray™ and the logos are trademarks of the Blu-ray Disc Association. *Amazon, Alexa and all related logos are trademarks of Amazon.com, Inc. or its affiliates. *Google, Chromecast Built-in, and related marks and logos are trademarks of Google LLC. The Google Assistant requires an internet connection and is not available in certain languages or countries. Controlling certain devices in your home requires compatible smart devices. Subscriptions for services and applications may be required and additional terms, conditions and/or charges may apply. *The HDR10+™ logo is a trademark or registered trademark of HDR10+ Technologies, LLC in the United States and other countries. *Dirac Live® is a registered trademark of Dirac Research AB protected by Swedish and international trademark laws and treaties. *Roon is a trademark of Roon, LLC, registered in the U.S. and other countries.

Apple AirPlay 2

Apple AirPlay 2 lets you effortlessly stream music or podcasts to speakers throughout your house using any Apple device or by asking Siri, and it all stays in perfect sync.



Advanced MCACC Auto Room Tuning featuring Auto Phase Control Plus

Advanced MCACC adjusts the sound according to the listening room and speakers, and also creates clearer sound by suppressing the standing waves that occur between walls or ceiling and floor. Measurement of up to nine positions can be saved for a wide listening area. Auto Phase Control Plus* makes real-time analysis of the phase difference, and automatically compensates the gap between the LFE and main signals, providing strong bass and clear high-frequency sound.



* Effectiveness depends on content

Works with SONOS

By bringing the VSX-LX505 into the Sonos eco-system with Connect or Port, you can play any music or audio source on your Sonos app. With "Volume Pass Through" mode selected at the Sonos App settings, you'll be able to control the volume of the unit by Sonos app or by itself. Enjoy high-quality playback from the AV receiver by Sonos app, just as you would with your favorite Sonos system. *Connection of maximum 3 Sonos devices is supported

Powered Zone 2/Zone 3

With the powered feature, the VSX-LX505 can directly drive speakers in other rooms, without the need for a separate amplifier. What's more, the dedicated DAC for Zone 2 lets you listen to all digital audio sources.



Zone B Output for Wireless Headphones

The VSX-LX505 is equipped with Zone B audio output terminals for expanding the Main Zone sound. You can listen to the sound playing in the living room via wireless headphones.



Voice Control

The VSX-LX505 features work with Google Assistant, so you can control playback of various music services supported by Chromecast by asking a Google Assistant enabled device to play, stop, skip, or take the volume up or down. This receiver also works with Alexa, so you can also use voice commands to control music services supported by Alexa built-in devices. Thanks to both voice controls, you can easily operate and enjoy music services or Internet radio with your voice, without using a remote control or smartphone app.

